

OB15

GENERAL

Category: Coach S

Maximum of cameras: 6 camera

DIMENSIONS

Length: 7,60m

Height: 3,60m

Width: 2,40m

Weight: 5,6 ton

POWER

Voltage: 32 amps 380/400 Volt
3phase + N / 50hz

Connector type: 32A CEE form

Cable: 50m Power cable

UPS system: VICTRON Battery
system 8KVA

Generator: PTO 3phase

SEATING POSITIONS

Production: 6

Sound room: 2

VIDEO

CAMERAS

18 HD cam on Triax / Fiber:

Grass Valley LDX 80/86/86N
SONY HDC 3500/4300

Wireless: Livetools

Lenses: 14x, 22x, 72x, 86x, 95x,
100x

VIDEO ROUTER

ROSS ULTRIX Hybrid
12G/3G/HD 105*105 with 4 MV
heads

Black Magic 20*20

Ross ASI router 16*16 C40

ETL L-band router 16*16

AXON Cerebrum controller

VISION MIXER

GVG Kula UHD / 3G

3*ME 3G / 1*ME UHD
(2ME 16 button panel)

inputs: 40

outputs: 14

aux buses: 10

10ch x Playout

4 Keyer/chromakey / ME, For-
mat Fusion, 1 ME UHD, 1 MV
4*DVE /ME , 2.5D DVE/sub ME

VIDEO RECORD REPLAY

2 * VTR positions
1 * USB recorder
1 * EVS LSM position

GRAPHICS

1 Position:
VIZRT , Chyron , Clarity

VIDEO CONNECTIVITY

1 * Stageracer 12ch CCU rack
on Fiberco 4ch Single mode
connector
1 * Stageracer 8ch Stand up
box on Fiberco 4ch Single
mode connectorB67
26 * 3G Externals

VIDEO MONITORING

Production front: 2* Sony 43"
Vision: 1* TV Logic LUM-240G 12G + 1* HP z23
Engineering: 2* z23 + TEK WVR8100
Flex : 2* 14"
Sound: 2* HP 23" 8-Split
2* HP Z23 KVM

SATELLITE/ TRANSMISSION

8 * Encoder positions 2 * 400 watt HPA
4 * Modulator position 1 off-air antenna
(DVB-S2-/NS3/NS4) 2 * 4channel L-band combiner/
4 * Decoder positions C81 upconverter
1 * Sat-lite antenna 2041 (L-band and ASI router
2meter)

GLUE WARE

Ross ULTRIX Embedding / Deembedding over Madi
8 * ULTRIX Framestore
Axon SYNAPSE
UXU400 , GXG400, GDS100, 2* XH100 C63
Emerson KVM router

AUDIO MIXER

Yamaha CL3

AUDIO CONNECTIVITY

2 * Rio 1608 stagebox dante 16x Mic/Line in - 8x out on SM 4ch Fiberco
1 * Stageracer 8 Mic/Line in/ 4x Riedel Intercom on BNC/ 4 GPI-O
+ 2 x 4-wire on SM 4ch Fiberco
1 * Stageracer CCU-Rack on SM 4ch Fiberco
1 * External Madi 32ch MM Fiberco/BNC
Redundant Riedel ring + AES67 on 2x SM 4ch FibercoB95

AUDIO MONITORING

Sound:

2 * Neumann KH 80 DSP
1 * Wholer

Production:

Genelec 2.0C101
1 * Fostex

AUDIO OUTBOARD

Spoton playback software Madi
DVS

COMMUNICATION

Intercom matrix:	Riedel Artist 32
Coax Panel ports:	8 * Coax Ports
Panels Internal	7
Panels External	1
Analog 4W	8
Analog 4W	16
GSM hybride	3
Motorola GM360 basestation (TX/RX)	2
Motorola GP340 Walkie Talkie	6
BOLERO Wireless Intercom	on request